

## Overview

Thank you for purchasing the Wireless QWERTY Keyboard & TouchPad Combo. You can use it for emails, chat, or to enjoy your favorite games. It is compatible with HTPC, Smart TV, TV BOX running Android systems. It also supports the Sony Playstation3. Use it with your HTPC on your Sofa or browse the internet in the most comfortable fashion.

## Product Image



## Package Contents

- Wireless Keyboard
- USB Wireless Receiver
- User Manual
- USB Charging Cable

## System Requirements

- HID compatible device
- USB port
- Windows 2000
- Windows XP
- Windows Vista, Windows CE, Windows 7, Windows 8

- Linux (Debian-3.1, Redhat-9.0, Ubuntu-8.10 Fedora-7.0 tested)
- Android OS (With standard USB interface)

## Specifications

Receiver (dongle): Nano style  
Connect Port: With USB2.0 above  
RF Mode: 2.4Ghz GFSK  
Transmission Distance: Up to 10 meters  
Transmission Power: Less than +4db  
Power Supply: Rechargeable 280mAh Polymer Lithium-ion Battery  
Charging Voltage: 4.4V ~ 5.25V  
Charging Current: 300mA  
Sleeping Current: 86uA  
Operation Voltage: 3.3V  
Product Weight: 210g  
Product Size: 260\*83\*13.5mm

## Installation

### 2.4G mode:

- Open the gift box and pick up USB receiver from back cover of the keyboard.
- Insert the USB receiver into an available USB port.
- Turn on the keyboard. The keyboard will be found automatically. No further actions are required – you are now ready to use your keyboard!

**NOTE:** USB cable can be used for battery charging

## Connecting the receiver

Slide the receiver out from the side of keyboard, and insert into the devices with a standard USB interface. Once inserted, slide the power switch to the "ON" position located on the left side of the unit to establish the connection.

## Bluetooth Mode:

### Microsoft Windows Mobile OS

#### Setup:

1. Connect your mobile device to your computer using the USB port.
2. On your PC, insert the Driver CD and access the drive by clicking on "My Computer"
3. Locate the "Mobile" folder and inside the "windowmobile.cab" (Bluetooth input driver) CAB file.
4. Open ActiveSync on your desktop and Click Explore
5. Copy the CAB file to your mobile device. You can do this by dragging and dropping the file from the desktop folder to My Documents folder on your device.
6. On the device, click on Start, Program, File Explorer, My Documents.
7. Run the windowmobile.cab file by tapping on it.
8. The Bluetooth keyboard drivers will install on your device.
9. After your device is reset, ensure the keyboard is in pairing mode.
10. On the device open "Bluetooth Devices" and click "Add New".
11. After the keyboard is discovered, select it and then tap on "Next".
12. When prompted for the passkey leave the field blank and click on "Next" if the pairing fails, repeat this step and use "0000" as the passcode.
13. Ensure "Input Device" is checked and tap on "Finish".
14. Go to the Software settings panel and tap on "Connect".

#### Troubleshooting:

The software is not responding: you need to reinstall this software-This error is caused by a problem with the communication between the software components. Check to ensure your Windows Mobile Device is supported by the keyboard (Version 5.0 or higher) and try to reinstall the software. Bluetooth is turned off-Bluetooth needs to be enabled in order to use this device. Make sure to turn it on in the settings menu.

No active input device found-Make sure the keyboard is properly paired with your smartphone.

#### Settings:

To open the setting menu, tap on Start, Settings, System and tap the icon named "Bluetooth Input Driver".

#### Keyboard Page:

This page allows you to enable or disable the keyboard functionality and sounds.

#### Status Page:

Allows you to view the status and autostart when windows mobile starts.

#### About:

Displays the software version and other useful info.

## Google Android OS

#### Setup:

1. On your PC, insert the Driver CD and access the drive by clicking on "My Computer".
2. Open the "Android" folder and copy the file labeled "android.apk" to your android's memory card.
3. On your device, open "Market" and install the "AppManager" Software.
4. Tap Install from SD option and run the "android.apk" file.
5. You will be presented with a screen requesting activation. Make sure to click "OK" with an active internet connection.
6. Make sure your Bluetooth mini keyboard is in the pairing mode and access the "Bluetooth Keyboard" icon under the main menu.
7. Make sure that Bluetooth is turned on and tap on "Search and Connect". The software will automatically find the keyboard and connect to it.

# MINI toetsenbord.nl

#### Troubleshooting:

Keyboard Disconnected-If your device loses the connection with the keyboard, you can reconnect by pressing the reconnect button.

#### Symbian OS:

##### Setup

1. On your PC, insert the Driver CD and access the drive by clicking on "My Computer".
2. Open the "Nokia Wireless Keyboard Application" folder on the CD and choose your device model by operating system version.
3. Copy the .sis file to your device's memory card or directly to the device via a USB cable.
4. On the device, find the .sis file and select it. Follow the onscreen instructions for installation.
5. Run the installed application-Wireless Keyboard and search for nearby Bluetooth devices.
6. After the device is paired and connected you may need to set the keyboard layout.

#### Windows OS(IVT Bluetooth Stack)

##### Setup

1. Make sure that Bluetooth is enabled on your PC.
2. Double click on the Bluetooth icon and select "Bluetooth Device Discovery".
3. Right click on the Bluetooth keyboard found and click on "Refresh Services".
4. Right click on the Bluetooth keyboard and select "Connect-Bluetooth Input Service".
5. A popup dialog will appear with a code. Input this code to the keyboard and press OK. The system will automatically install the drivers for the keyboard.

#### Windows OS(Broadcom Bluetooth stack)

1. Make sure that the Bluetooth function is active on your PC. Double click the Bluetooth icon, then click "View devices in range".
2. Click "Search devices in range" and wait until the Mini Bluetooth keyboard is discovered.
3. Right clicking the detected keyboard brings a popup menu. Click "Connect device".
4. Press YES to connect to the "Human interface Device".
5. Using the Mini Bluetooth keyboard, type the number displayed on the screen, then press enter.

#### Linux(Ubuntu)

1. Make sure that the Bluetooth function is active on your PC. Click the Bluetooth icon and select "Setup new device". A wizard window opens, read the text and press "Forward".
2. Wait until the keyboard is discovered, then select it and press "Forward".
3. Type the code displayed on the Mini Bluetooth keyboard, then press "Enter".

#### Basic functions

##### (1) Primary Key bits

The function printed at each key is defaulted by pressing the button with one time.

##### (2) Sub-keys

Press the SHIFT key while using these keys, including !, @, #, \$, %, ^, &, \*, (, ), ~, |, ", {, }, ?, \_ , +

##### (3) Compound keys

Press the FN key while using these keys, all these keys were printed in Blue for easy recognize.

#### (4) Touchpad

This touchpad supports multi-finger functions.

- (1) When a single finger clicks, left mouse activated
- (2) When two-finger clicks, right mouse activated
- (3) When two-finger clicks, right mouse activated
- (4) When a single finger double-clicks, you can open the file where the cursor is positioned.

#### Auto sleep and wake up feature

The keyboard also has an auto sleep and wake up feature. Within three minutes, if no keys pressed, the keyboard will automatically go into sleep mode. In sleep mode, all lights being in extinguished state. Users can click on any key to activate the device.

#### Switching off the keyboard after use

After using the keyboard, push the switch to the "OFF" position. This turns off the keyboard. The USB receiver does not need to be pulled out from the PC. You can use it directly next time.

#### Charging the battery

The device uses built-in lithium-ion battery. Please use only approved data cables and chargers.

Note: Fully charge the unit before initial operation. This device can be used when charging, but charging time will be extended.

When the battery is low, the low-voltage light will blink to warn the user. The unit will be automatically turned off if the battery has been depleted.

#### Warning

- When charging finishes, pull out the charge cable.
- Never try to open or repair this product yourself.
- Keep this device away from fluids, such as water.

#### Maintenance

- Do not attempt to disassemble the device or replace the rechargeable battery. Doing so will void the warranty.
- The battery will discharge if it is stored for a long time without operation.
- Use the specified charger. Disconnect the device when the battery is fully charged. Overcharging the battery will shorten the battery life.
- Do not expose the device in extreme heat or cold environment, which will shorten the battery life.

#### Disposal



Always dispose the used appliance at a recycling centre. Do not dispose the used appliance together with the household waste.

#### Note:

Due to the device uses 2.4G radio waves technology to communicate, the connection can be subject to interference from obstacles, like walls, metals, or other electronic devices, so please keep the keyboard and dongle in a line as possible.

In line with the policy of continued development, the manufacturer reserves the right to amend the specifications without prior notification. The illustrations in the user manual are for reference only. Please operate according to the real design.